

## HELP = Command List for DX Net Software / BCARES Cluster

A command can be shortened by using only the letters shown in **CAPITALS**

You can obtain a detailed help about any command by typing:

? {cmd} (example: ? SH/U or ? SH for extra help on all SH/xxx)

---

<b>HELP</b>	Show this list of commands for the cluster software
<b>List</b>	Shows ALL messages – do you need to see them all?
<b>LL</b> {#}	Show the last # messages (ie: “LL 5” will list the last <u>5</u> messages)
<b>LM</b>	Show all messages addressed to me
<b>LN</b>	Show the new messages addressed to me
<b>L&gt;</b> {recipient}	Show all messages addressed to {recipient}
<b>L&lt;</b> {sender}	Show all messages sent by {sender}
<b>LS</b> {title}	Show all message containing {title} in title
<b>Read</b> {#}	Read a message by it’s number
<b>Kill</b> {#}	Kill or delete the message by that number
<b>Send</b> {callsign}	Send a message to [callsign]
<b>Talk</b> {callsign}	* Send a break message to [callsign]
<b>CONFerence</b>	* Enter the local conference
<b>CONFerence/Full</b>	* Enter the cluster-wide conferences
<b>Announce</b> {msg}	* Send a local announcement
<b>Announce/Full</b> {msg}	* Send a cluster-wide announcement
<b>SHow/Announce</b>	Announcement list
<b>SHow/CLuster</b>	Show Cluster configuration
<b>SHow/ConfiguratiOn</b>	Cluster configuration
<b>SHow/Date</b>	See the current date
<b>SHow/Time</b>	Show the current time
<b>SHow/Users</b>	Local cluster configuration
<b>SHow/WWV</b>	Shows WWV updates & reports
<b>SET/Here</b>	You're here (your location)
<b>SET/NOHere</b>	You're away
<b>SET/NAME</b> {name}	Set your first name
<b>SET/QTH</b> {city}	Set your QTH
<b>SET/PAGE</b> {0 - 255}	Set page length before [CR] is required [SET/PAGE 255 = continuous]
<b>Bye (or Quit)</b>	Quit or Log off

**Tactical call signs** are no longer allowed on the cluster. You must use a valid FCC call sign. Your personal sign is your best choice unless you have an assigned BCARES call sign related to your assignment.

---

For **RMS** Nodes use similar commands but you are pretty much limited to:

**HELP I LM RM R## K## KM SP Bye**

The use of properly designed software is recommended, especially for formatting and sending messages.

The un-censored list ~ some may not work...

<b>S</b> How/Announce	Announcement list
<b>S</b> How/Beam <locator>	Show azimuth/distance
<b>S</b> How/BAsE or /DATAbase	Available Databases on this cluster
<b>S</b> How/CLuster	Show Cluster information
<b>S</b> How/Configuration	Cluster Configuration
<b>S</b> How/Date	See current date
<b>S</b> How/DX	See the 5 last spots
<b>S</b> How/DX/n [band] [prefix]	See the n last spots (see detailed help: ? SH/DX)
<b>S</b> How/Filter	See the DX announcement status
<b>S</b> How/LANGUage	Language list
<b>S</b> How/Prefix <prefix>	Search the DXCC database
<b>S</b> How/STation <callsign>	Display information for the station call
<b>S</b> How/Time	Show the current time
<b>S</b> How/Users	Local cluster users on line
<b>S</b> How/USERCmd	Display the commands executed at logging
<b>S</b> How/WWFilter	Show your WW filter status
<b>S</b> How/WWV	Display WWV propagation information
<b>S</b> ET/BEep [d] [a] [t] [l] [w]	Enable BEEP alerts
<b>S</b> ET/DX_announcements	Enable the DX announcements
<b>S</b> ET/Filter <...>	Enable a DX announcement filter
<b>S</b> ET/Here	You're here
<b>S</b> ET/NOHere	You're away
<b>S</b> ET/HOME <cluster_call>	Set your home cluster
<b>S</b> ET/LANGUage <num_language>	Set the language (see sh/lang)
<b>S</b> ET/LOCator <locator>	Set your locator
<b>S</b> ET/LOGIn	Enable login/logout messages
<b>S</b> ET/NAME <name>	Set your first name
<b>S</b> ET/NOBeep [d] [a] [t] [l] [w]	Disable BEEP alerts
<b>S</b> ET/NODX_announcements	Disable the DX announcements
<b>S</b> ET/NOFilter	Disable the DX announcement filter
<b>S</b> ET/NOLogin	Disable login/logout messages
<b>S</b> ET/NOWwfilter	Disable the WW announcements feature
<b>S</b> ET/PAGE <0 to 255>	Set page length befor <CR> is required
<b>S</b> ET/QTH <city>	Set your QTH
<b>S</b> ET/USERCmd	Set the commands which are executed at login
<b>A</b> nnounce <msg>	Send a local announcement
<b>A</b> nnounce/Full <msg>	Send a cluster-wide announcement
<b>B</b> ye (or Quit)	Log off or Quit
<b>C</b> ONference	Enter the local conference
<b>C</b> ONference/Full	Enter the cluster-wide conference
<b>C</b> ONvert/L2C	Convert a locator to coordinates
<b>C</b> ONvert/C2L	Convert coordinates to a locator
<b>D</b> X <freq> <dxcall> [comments]	Send a DX spot [freq is in Khz]
<b>E</b> U	Edit user information
<b>I</b> nformation	Display the information about the server
<b>K</b> ill <#>	Kill (delete) a message
<b>L</b> ist	Show the new messages
<b>L</b> L <#>	Show the last # messages
<b>L</b> M	Show the whole message addressed to me
<b>L</b> N	Show the new mail messages addressed to me
<b>L</b> > <recipient>	Show all messages addressed to <recipient>
<b>L</b> < <sender>	Show all messages sent by <sender>
<b>L</b> S <title>	Show all message containing <title> in title
<b>R</b> ead <#>	Read a message
<b>S</b> end <callsign>[@cluster]	Send a message
<b>T</b> alk [callsign]	Send a break message to [callsign]
<b>W</b> WV <SFI> <A> <K> [comments]	Send a WWV propagation information
<b>Other Help:</b>	
Access to Databases:	Enter ? BASE for help on the Databases
Messaging commands:	Enter ? MSG for help on the messaging commands.

You can obtain a detailed help about any command by typing:  
? [cmd] (example: ? SH/DX or ? SH for extra help on all SH/xxx)  
A command can be shortened by using only the bold letters.